

DSRM-E1P

Edit Adaptor

- Direct connection to the DSR-V10P via a 20-pin connector
- Controls LANC VTRs as players (DSR-PD1P/ DSR-20P/ DSR-30P)
- Built-in Jog/Shuttle dial
- Assemble editing with up to 99 events x 4 programmes

Downloaded from: www.broadcast-trader.com.au

GENERAL

Power requirements: DC:7.2 V (supplied from the DSR-V10P)
DC:8.4 V (AC adaptor operation)

Power consumption: Approx. 1.8 W

Operating temperature:

0 °C to 40 °C (32 °F-104 °F)

Storage temperature: -20 °C to 60 °C (-4 °F-140 °F)

Mass: Main Unit: 160 g (5.6 oz)

Controller: 340 g (12 oz)

Dimensions:

Main Unit: 134.4 (W) × 69.2 (H) × 60.6 (D) mm
(5 3/8 × 2 3/4 × 2 1/2 inches)

Controller: 128.1 (W) × 184 (H) × 42 (D) mm
(5 1/8 × 7 1/4 × 1 11/16 inches)

CONNECTORS

DSR-V10P: 20-pin

Control Unit: Mini DIN 8-pin

LANC: Stereo mini-mini jack

MONITOR OUTPUT

Video Output: Composite (RCA phono jack (1)):
1.0 V p-p, 75 Ω, unbalanced, sync
negative

Audio Output: RCA phono jack (2) (L, R):
327 mV, impedance 470 Ω or less

