

## IF-FXE2

### LANC Interface Box

- Converts the RS-422A protocol to LANC protocol
- Supports connection between recorder LANC VTR's and FXE-100UPG\*1/FXE-120
- Supports connection between player LANC VTR's and RM-450/PVE-500
- Allows easy system integration of the DSR-30/200 (DVCAM format) and LANC VTR's

\*1 FXE-100UGP is an FXE-100 which is upgraded with FXE-KIT1.  
Please contact your nearest Sony office.

Supplied Accessories: LANC Connecting Cord (Stereo mini-mini) (1)  
AC Power Adaptor (1)  
Instruction Manual (1)  
List of the recommended products (1)

Optional Accessories: RS-422 Remote Control Cable: RCC-5G/10G/30G

### Specifications

#### General

Mass: Approx. 500 g (17.6 oz)  
Dimensions: Approx. 106 (W) × 40 (H) × 163 (D) mm  
(4 1/4 × 1 5/8 × 6 1/2 inches)  
Power requirements: DC 6 V  
Power consumption: Less than 3W (with the supplied AC power adaptor)  
Operating temperature: 5 C to 40°C  
Storage temperature: -20 C to 60°C  
Operational position: Horizontal or vertical

#### Connectors

RS-422A port: D Sub 9-pin (1)  
LANC port: Stereo mini-mini jack (1)  
DC input: 6V (1)

#### Function Switches

Power: Seesaw Switch (1)  
Learn: Push Switch (1) and LED (1)  
Preset: Dip Switch (4bit)



Downloaded from: [www.broadcast-trader.com.au](http://www.broadcast-trader.com.au)