

**20 PVM-20N6E/20N6A\*1** (PAL/NTSC/SECAM/NTSC<sup>4,43</sup>)  
**Colour Video Monitor**

- Resolution of 500TV lines
- Beam current feedback circuit for stability in the colour balance
- Accepts composite video, Y/C and RGB signals
- Switchable aspect ratio (4:3 and 16:9)
- On-screen menu for adjustment/operation
- Input channel can be selected via REMOTE terminal (Phono)
- Built-in speaker
- One touch recall of last menu used (VOLUME, CONTRAST, BRIGHTNESS, CHROMA and PHASE)
- Mountable into a 19-inch EIA standard rack with the optional SLR-103A

Optional accessories: Slide rail kit SLR-103A

**Specifications**

Video signal system: CCIR 625 lines, 50 fields/EIA 525 lines, 60 fields (switching of CCIR to EIA or vice versa is automatically done)

Colour system: PAL/NTSC/SECAM/NTSC<sup>4,43,2</sup>

Picture tube: 53 cm(20-inch), visible picture size 48.0 cm (min.) (19-inch) measured diagonally, 90° deflection

Horizontal resolution: 500TV lines at centre

Audio power output: Monaural, 0.8W with built-in speaker

Power requirements: AC 100 to 240V, 50/60Hz

Power consumption: 105W

Dimensions: 449(W) x 441(H) x 502(D) mm (17 1/8 x 17 3/8 x 19 3/4 inches)

Mass: 28 kg (61 lb 11 oz)

**VIDEO**

LINE A\*<sup>3</sup> Loop-through BNC  
 1.0Vp-p, sync negative, Automatic 75Ω termination\*<sup>4</sup>  
 Loop-through Mini DIN 4-pin  
 Y (luminance): 1.0Vp-p, sync negative, Automatic 75Ω termination\*<sup>4</sup>  
 C (chrominance): PAL: 0.3Vp-p, Automatic 75Ω termination\*<sup>4</sup>  
 NTSC: 0.286Vp-p, Automatic 75Ω termination\*<sup>4</sup>

LINE B\*<sup>3</sup> BNC  
 1.0Vp-p, sync negative, 75Ω  
 Mini DIN 4-pin  
 Y: 1.0Vp-p, sync negative, 75Ω  
 C: PAL: 0.3Vp-p, sync negative, 75Ω  
 NTSC: 0.286Vp-p, 75Ω

RGB/Sync BNC  
 R/G/B: 0.7Vp-p, 75Ω  
 Sync on G: 0.3Vp-p, 75Ω  
 Sync: 4Vp-p, 75Ω

**AUDIO**

LINE A Loop-through Phono  
 -5dBu, high impedance

LINE B Phono  
 -5dBu, high impedance

RGB/Sync Phono  
 -5dBu, high impedance

Downloaded from: [www.broadcast-trader.com.au](http://www.broadcast-trader.com.au)

